

GV-Joystick V2



GV-Joystick V2 is a plug-and-play device for panning, tilting, zooming, and focusing a PTZ camera. It is compatible not only with GeoVision software, but also with any third-party software that supports the HID standard.

Specifications

OS Supported	32-bit	Windows 7 / 8 / 10 / Server 2008
	64-bit	Windows 7 / 8 / 10 / Server 2008 R2 / Server 2012 / Server 2016 / Server 2019
Communication	USB	Connects to PC
	RJ-45	Connects to GV-Keyboard V3
Power	DC IN	DC 5V 50mA
Environmental Conditions	Operation Temperature	0 ~ 50°C / 32 ~ 122°F
	Humidity	5% ~ 95% (non-condensing)
Dimensions (W x H x D)		160 x 90 x 118 mm (6.3 x 3.54 x 4.65")
Weight		500 g (1.1 lb)

Note:

1. When connected to GV-NVR / GV-VMS / GV-Edge Recording Manager, GV-Joystick V2 can control third-party ONVIF PTZ cameras.
2. When connected to GV-NVR / GV-VMS, GV-Joystick V2 can control TVI / AHD PTZ cameras connected via GV-VS2400 / 2420 / 2800 by coaxial cables.
3. All specifications are subject to change without notice.

Compatible GeoVision Products

- GV-NVR V8.5.9 or later
- GV-VMS
- GV-Edge Recording Manager (Windows version) V2.0.0 or later
- GV-Center V2 V8.5.9 or later
- GV-Control Center and GV-Video Wall V3.1.2 or later
- GV-SNVR: GV-SNVR0411 / 0811 / 0412 / 0812 / 1611
- GV-IP Decoder Box and GV-Pad firmware V1.06 or later
- GV-IP Decoder Box Plus firmware V1.00 or later
- GV-Keyboard V3 firmware V3.0.0.1 or later

Packing List

- GV-Joystick V2
- USB Type A to Type B Cable